

EARTH CONTINUITY RELAY 'IC1'



Features:

The IC1 has been designed to provide Earth Continuity monitoring of a supply cable by grounding the load end of the pilot core via a diode to earth. Local/Remote start operation is selectable.

Earth Continuity Features:

- Operational 45 ohms max.
- Excellent tolerance to pilot cable capacitance and inductance allowing longer cable runs.
- Pilot to Earth termination using 1A diode.
- IC1 Relay is closed when pilot circuit is healthy .
- Local/Remote Start pilot operation switch selectable. Remote Start/Stop using a 100R start resistor.
- Status Leds for -
 - RY On
 - Power
 - Pilot Open
 - Pilot Closed
 - Pilot Short
 - Ready
- 2 sets C/O contacts are provided.

Specifications:

Power Input: 110/240V AC 2VA
optional: 240V AC
optional: 24 - 48V AC/DC - 50VAC Max

Pilot to Earth Resistance :
EC Mode: 45 ohms maximum

Remote Start Mode: 145 ohms max

Start Resistance: 100 ohms

Specifications cont.

Shunt Resistance for Trip: Less than 1K ohms

Trip Delay: 500mS

Relay Contacts

2 x Changeover
5A - 240V AC

Operating Temp: 0 - 60 Deg Celcius

Enclosure:

Dimensions: 55W x 75H x 110D
Material: Himpact resistant polycarbonate construction.
Mounting: Din Rail and screw mounting.
Terminals: Cage screw terminals.
Weight: 200gm.

Ordering:

A01047 - 110V AC
A01049 - 240V AC
A01048 - 24 - 48V AC or DC

This product is designed and manufactured by an ISO9001:2000 certified company.

Bramco Contacts

Bramco International
16 Templar Place
Bennetts Green 2290
www.bramco.com.au

Telephone (02) 49544721
Email info@bramco.com.au



REMOTE START ARRANGEMENT

